



EF86/EF806*	G3	G2	G2	SC	C	HT1	HT2	P	SC
12BH7**	C2	HCT	P1	G1	C1	HT1	HT2	P2	G2
12DW7*	C2	HCT	P1	G1	C1	HT1	HT2	P2	G2
6C45Pi***	G	C	C	G	C	HT1	HT2	C	P
6H30Pi	C2	SC	P1	G1	C1	HT1	HT2	P2	G2
ECC99*	C2	HCT	P1	G1	C1	HT1	HT2	P2	G2
ECC88/6922/6DJ8*	C2	HCT	P1	G1	C1	HT1	HT2	P2	G2
EZ81*	NC	NC	P1	NC	C	HT1	HT2	NC	P2

ABBREVIATION KEY

P = PLATE
 C = CATHODE
 G = GRID
 SC = SCREEN
 HT = HEATER
 HCT = HEATER CENTER TAP
 NC = NOT CONNECTED

*PINOUT OBTAINED FROM THE JJ ELECTRONICS TUBE DATA BOOK.
 **PINOUT OBTAINED FROM WWW.EIRC.COM.
 ***PINOUT OBTAINED FROM WWW.THETUBESTORE.COM.

TRENTON
BLIZZARD

BB-NOVAL PINOUT

© Copyright 2007 Trenton Blizzard Designs